



ACCESSORIES



IP65 ACCESSORY



ADD-ON BEZEL

AWARDS



PRODUCT

Name	SWAP S 5W 3500K G
Reference	A2121113G
Color	Gold
RAL	1036
Category	CEILING RECESSED

LIGHT SOURCE

Type	LED
Gross luminous flux	705 lm
Colour temperature	3500 K
Chromatic stability	MacAdam Step 2
Colour Rendering Index	CRI > 90
Power	5 W
Current	150 mA
Efficacy	141 lm/W
LED lifespan	L90B10 > 55.000h

LIGHTING FIXTURE | PHOTOMETRIC DATA

Lighting efficiency	77%
Light beam angle	33°

LIGHTING FIXTURE | ELECTRICAL DATA

Driver	Included - Fast Connect
Power values of the system	5,83 W
Frequency	50/60 Hz
Dimming	No Dim - Other DIM, please consult
Electrical insulation class	☐


OTHER DATA

Sealing	IP20
Wireless control	Please Consult
Emergency power supply	Please Consult
Impact resistance	IK07
Recess measurements	Ø62 mm
Weight	200 g
Packaged weight	233,5 g
Packaging dimensions	94 x 88 x 93 mm
Units per package	1
Materials	Aluminium / Polycarbonate




Swap is a ceiling recessed LED spotlight whose main features are its minimalist aspect, its perfect integration into the ceiling, and considerable visual comfort, thanks to the small reflector that is set back with respect to the ceiling plane. When it is switched on, its matte finish shade generates an attractive effect, a discrete circle of light. It includes an add-on bezel that can be used optionally to cover larger recess diameters.

POLAR DIAGRAM



CONICAL DIAGRAM



UGR

Glare Evaluation According to UGR												
ρ Ceiling		70	70	50	50	30	70	70	50	50	30	30
ρ Walls		50	30	50	30	30	50	30	50	30	30	30
ρ Floor		20	20	20	20	20	20	20	20	20	20	20
Room Size X Y		Viewing direction at right angles to lamp axis					Viewing direction parallel to lamp axis					
2H	2H	17.3	18.1	17.5	18.3	18.5	17.3	18.1	17.5	18.3	18.5	
	3H	19.2	19.9	19.5	20.2	20.4	19.2	19.9	19.5	20.2	20.4	
	4H	20.0	20.7	20.3	21.0	21.2	20.0	20.7	20.3	21.0	21.2	
	6H	20.7	21.4	21.1	21.7	22.0	20.7	21.4	21.1	21.7	22.0	
	8H	21.1	21.7	21.4	22.0	22.3	21.1	21.7	21.4	22.0	22.3	
4H	12H	21.4	22.0	21.7	22.3	22.6	21.4	22.0	21.7	22.3	22.6	
	2H	17.9	18.6	18.2	18.9	19.1	17.9	18.6	18.2	18.9	19.1	
	3H	20.0	20.6	20.4	20.9	21.3	20.0	20.6	20.4	20.9	21.3	
	4H	21.0	21.5	21.4	21.9	22.2	21.0	21.5	21.4	21.9	22.2	
	6H	21.9	22.4	22.3	22.7	23.1	21.9	22.4	22.3	22.7	23.1	
8H	8H	22.3	22.7	22.8	23.1	23.5	22.3	22.7	22.8	23.1	23.5	
	12H	22.7	23.1	23.2	23.5	23.9	22.7	23.1	23.2	23.5	23.9	
	4H	21.4	21.8	21.8	22.2	22.6	21.4	21.8	21.8	22.2	22.6	
	6H	22.5	22.8	23.0	23.2	23.7	22.5	22.8	23.0	23.2	23.7	
	8H	23.0	23.3	23.5	23.7	24.2	23.0	23.3	23.5	23.7	24.2	
12H	12H	23.6	23.8	24.1	24.2	24.7	23.6	23.8	24.1	24.2	24.7	
	4H	21.5	21.8	21.9	22.2	22.6	21.5	21.8	21.9	22.2	22.6	
	6H	22.6	22.9	23.1	23.3	23.8	22.6	22.9	23.1	23.3	23.8	
	8H	23.2	23.4	23.7	23.9	24.4	23.2	23.4	23.7	23.9	24.4	
Variation of the observer position for the luminaire distances S												
S = 1.0H S = 1.5H S = 2.0H		+0.2 / -0.1 +0.4 / -0.3 +0.6 / -0.6					+0.2 / -0.1 +0.4 / -0.3 +0.6 / -0.6					
Standard table		BK07					BK07					
Correction Summand		6.2					6.2					
Corrected Glare Indices referring to 705lm Total Luminous Flux												



Fuente de luz (LED) reemplazable por un profesional autorizado

Replaceable (LED only) light source by an authorized professional.

Source lumineuse (LED) remplaçable par un professionnel agréé

Sorgente luminosa (LED) sostituibile da parte di un professionista autorizzato

Austauschbare (LED) Lichtquelle durch einen autorisierten Fachmann



Equipo de control reemplazable por un profesional autorizado

Replaceable control gear by an authorized professional

Dispositif de commande remplaçable par un professionnel agréé

Alimentatore sostituibile da parte di un professionista autorizzato

Auswechselbares Betriebsgerät durch autorisierten Fachmann

INSTRUCCIONES PARA EL FINAL DE VIDA Y LA ELIMINACIÓN LOS COMPONENTES

INSTRUCTIONS ON END-OF-LIFE AND COMPONENT DISPOSAL

INSTRUCTIONS POUR LA GESTION DES COMPOSANTS EN FIN DE VIE ET LEUR MISE AU REBUT

ISTRUZIONI PER IL FINE VITA E LO SMALTIMENTO DEI COMPONENTI

ANWEISUNGEN ZUR ENTSORGUNG DER LEUCHTENKOMPONENTEN



Interrumpir la alimentación del aparato

Cut the power supply to the luminaire

Couper l'alimentation du luminaire

Interrompere l'alimentazione dell'apparecchio

Stromversorgung der Leuchte unterbrechen



Quitar la(s) fuente(s) de luz para el desecho

Remove light source(s) for disposal

Retirer la (les) source(s) lumineuse(s) pour l'élimination

Rimuovere la/le sorgente/e di luce per lo smaltimento

Lichtquelle(n) zur Entsorgung entfernen



Quitar la batería para el desecho

Remove the battery for decommissioning

Retirer la batterie pour sa mise au rebut

Rimuovere la batteria per la dismissione

Die Batterie ordnungsgemäß entsorgen



Quitar el equipo de control para el desecho

Remove control gear for disposal

Retirer le dispositif de commande pour l'élimination

Rimuovere l'alimentatore per lo smaltimento

Betriebsgerät zur Entsorgung ausbauen

Enviar los materiales a un centro de recogida RAEE

Send the materials to a WEEE collection centre

Envoyer les matériaux dans une déchetterie DEEE

Inviare i materiali ad un centro di raccolta RAEE

Die Materialien in einem WEEE-Zentrum entsorgen

