



### DIMENSIONES



### ACCESORIOS



WIRE TRIMLESS ACCESSORY



TRIMLESS TOOL

### PREMIOS

DESIGN  
AWARD  
2015GERMAN  
DESIGN  
AWARD  
NOMINEE  
2016

|            |                          |
|------------|--------------------------|
| Nombre     | SALT 5 DIM PUSH 4000K WR |
| Referencia | A2200522WR               |
| Color      | White-Red                |
| Color Base | Textured white           |
| RAL        | 9016 & 2004              |
| Categoría  | SUSPENSION               |

### FUENTE DE LUZ

|                                  |                  |
|----------------------------------|------------------|
| Tipo                             | LED              |
| Flujo Luminoso                   | 5225 lm          |
| Temperatura de color             | 4000 K           |
| Estabilidad cromática            | MacAdam Step 2   |
| Índice de reproducción cromática | CRI > 90         |
| Potencia                         | 35 W             |
| Corriente                        | 900 mA           |
| Eficacia                         | 149 lm/W         |
| Horas de Vida del LED            | L80B10 > 60.000h |

### LUMINARIA | DATOS FOTOMÉTRICOS

|                       |     |
|-----------------------|-----|
| Eficiencia Lumínica   | 79% |
| Ángulo del haz de luz | 77° |

### LUMINARIA | DATOS ELÉCTRICOS

|                              |           |
|------------------------------|-----------|
| Driver                       | Included  |
| Potencia del sistema         | 40,94 W   |
| Tensión                      | 220V/240V |
| Frecuencia                   | 50/60 Hz  |
| Regulación                   | Push      |
| Clase de seguridad eléctrica | ⚡         |

### OTROS DATOS

|                             |                                     |
|-----------------------------|-------------------------------------|
| Estanqueidad                | IP20                                |
| Control inalámbrico         | Please Consult                      |
| Longitud del cable          | Max. 2 m                            |
| Tensor de regulación rápida | Yes                                 |
| Peso                        | 4600 g                              |
| Peso con embalaje           | 5329,4 g                            |
| Dimensiones embalaje        | 452 x 452 x 418 mm                  |
| Unidades por embalaje       | 1                                   |
| Materiales                  | Aluminium / Polymethyl Methacrylate |



High Bay light fitting performance combined with the design of a unique decorative piece. Salt integrates driver and heat dissipation into the design of the fitting itself and achieves on the one hand an excellent thermal management and on the other hand the freedom to hang the fixture at any desired height. And to prevent glare, Salt disposes of a diffusor covering the light source.

DIAGRAMA POLAR



DIAGRAMA CÓNICO



UGR

| Glare Evaluation According to UGR                                |     |  |      |      |      |      |   |      |      |      |      |
|--|-----|--|------|------|------|------|---|------|------|------|------|
| ρ Ceiling  |     | 70   | 70   | 50   | 50   | 30   | 70                                      | 70   | 50   | 50   | 30   |
| ρ Walls  |     | 50   | 30   | 50   | 30   | 30   | 50                                      | 30   | 50   | 30   | 30   |
| ρ Floor  |     | 20   | 20   | 20   | 20   | 20   | 20                                      | 20   | 20   | 20   | 20   |
| Room Size X Y  |     | Viewing direction at right angles to lamp axis |      |      |      |      | Viewing direction parallel to lamp axis |      |      |      |      |
| 2H   | 2H  | 16.3   | 17.3 | 16.5 | 17.5 | 17.7 | 16.3                                    | 17.3 | 16.5 | 17.5 | 17.7 |
|  | 3H  | 18.1   | 19.0 | 18.4 | 19.3 | 19.5 | 18.1                                    | 19.0 | 18.4 | 19.3 | 19.5 |
|  | 4H  | 18.7   | 19.6 | 19.1 | 19.9 | 20.2 | 18.7                                    | 19.6 | 19.1 | 19.9 | 20.2 |
|  | 6H  | 19.3   | 20.1 | 19.6 | 20.4 | 20.7 | 19.3                                    | 20.1 | 19.6 | 20.4 | 20.7 |
|  | 8H  | 19.4   | 20.2 | 19.8 | 20.5 | 20.9 | 19.4                                    | 20.2 | 19.8 | 20.5 | 20.9 |
| 4H   | 12H | 19.6   | 20.3 | 19.9 | 20.6 | 21.0 | 19.6                                    | 20.3 | 19.9 | 20.6 | 21.0 |
|  | 2H  | 16.9   | 17.8 | 17.2 | 18.0 | 18.3 | 16.9                                    | 17.8 | 17.2 | 18.0 | 18.3 |
|  | 3H  | 18.9   | 19.6 | 19.2 | 20.0 | 20.3 | 18.9                                    | 19.6 | 19.2 | 20.0 | 20.3 |
|  | 4H  | 19.7   | 20.4 | 20.1 | 20.7 | 21.1 | 19.7                                    | 20.4 | 20.1 | 20.7 | 21.1 |
|  | 6H  | 20.3   | 20.9 | 20.8 | 21.3 | 21.7 | 20.3                                    | 20.9 | 20.8 | 21.3 | 21.7 |
| 8H   | 8H  | 20.6   | 21.1 | 21.0 | 21.5 | 21.9 | 20.6                                    | 21.1 | 21.0 | 21.5 | 21.9 |
|  | 12H | 20.8   | 21.2 | 21.2 | 21.7 | 22.1 | 20.8                                    | 21.2 | 21.2 | 21.7 | 22.1 |
|  | 4H  | 20.0   | 20.5 | 20.4 | 20.9 | 21.3 | 20.0                                    | 20.5 | 20.4 | 20.9 | 21.3 |
| 12H  | 6H  | 20.8   | 21.2 | 21.3 | 21.7 | 22.1 | 20.8                                    | 21.2 | 21.3 | 21.7 | 22.1 |
|  | 8H  | 21.1   | 21.5 | 21.6 | 21.9 | 22.4 | 21.1                                    | 21.5 | 21.6 | 21.9 | 22.4 |
|  | 12H | 21.4   | 21.7 | 21.9 | 22.2 | 22.7 | 21.4                                    | 21.7 | 21.9 | 22.2 | 22.7 |
| 12H  | 4H  | 20.0   | 20.5 | 20.5 | 20.9 | 21.3 | 20.0                                    | 20.5 | 20.5 | 20.9 | 21.3 |
|  | 6H  | 20.9   | 21.2 | 21.4 | 21.7 | 22.2 | 20.9                                    | 21.2 | 21.4 | 21.7 | 22.2 |
|  | 8H  | 21.3   | 21.6 | 21.7 | 22.0 | 22.5 | 21.3                                    | 21.6 | 21.7 | 22.0 | 22.5 |
| Variation of the observer position for the luminaire distances S |     |  |      |      |      |      |   |      |      |      |      |
| S = 1.0H   |     | +0.3 / -0.3                                    |      |      |      |      | +0.3 / -0.3                             |      |      |      |      |
| S = 1.5H   |     | +0.7 / -0.5                                    |      |      |      |      | +0.7 / -0.5                             |      |      |      |      |
| S = 2.0H   |     | +1.3 / -0.8                                    |      |      |      |      | +1.3 / -0.8                             |      |      |      |      |
| Standard table   |     | BK05   |      |      |      |      | BK05                                    |      |      |      |      |
| Correction Summand   |     | -2.8   |      |      |      |      | -2.8                                    |      |      |      |      |
| Corrected Glare Indices referring to 5225lm Total Luminous Flux  |     |  |      |      |      |      |   |      |      |      |      |

FEED



| PRODUCT   |   |
|-----------|---|
| Model     | Mains Trimless  |
| Reference | A023-00-01-   W   N   |
| Colour    | W <input type="checkbox"/> RAL 9016   N <input type="checkbox"/> RAL 9005 |
| Category  | Accessories   |



| PRODUCT   |   |
|-----------|---|
| Model     | Mains Thick Trimless  |
| Reference | A023-00-02-   W   N   |
| Colour    | W <input type="checkbox"/> RAL 9016   N <input type="checkbox"/> RAL 9005 |
| Category  | Accessories   |



Wire Trimless Accessory is a collection of accessories for fitting tensioners and cables to Arkoslight luminaires suspended directly from the ceiling with any visible ceiling rose or fixings. This achieves a minimalist application with a visually tidy finish.

With Wire Trimless Accessory the items adjacent to the ceiling of the standard product (ceiling roses, fixings, driver boxes, etc.) are concealed by a simple recessed application.

Wire Trimless Accessory reduces the visual impact of the installation leading to extremely minimalist aesthetics. The wires come out of the ceiling material as a part of the structure. This detail creates a much purer, more essential layout, particular when several luminaires are fitted in an arrangement.

FASTENING



| PRODUCT   |   |
|-----------|---|
| Model     | Steel Cable Trimless  |
| Reference | A023-00-05-   W   N   |
| Colour    | W <input type="checkbox"/> RAL 9016   N <input type="checkbox"/> RAL 9005 |
| Category  | Accessories   |

3 Pcs. needed



Wire Trimless Accessory is a collection of accessories for fitting tensioners and cables to Arkoslight luminaires suspended directly from the ceiling with any visible ceiling rose or fixings. This achieves a minimalist application with a visually tidy finish.

With Wire Trimless Accessory the items adjacent to the ceiling of the standard product (ceiling roses, fixings, driver boxes, etc.) are concealed by a simple recessed application.

Wire Trimless Accessory reduces the visual impact of the installation leading to extremely minimalist aesthetics. The wires come out of the ceiling material as a part of the structure. This detail creates a much purer, more essential layout, particular when several luminaires are fitted in an arrangement.



INSTALLATION GUIDE

[https://youtu.be/sa\\_xAgj4ji4](https://youtu.be/sa_xAgj4ji4)

## PRODUCT

|           |                            |
|-----------|----------------------------|
| Model     | Trimless Tool D20 X D52 MM |
| Reference | A478-00-01                 |
| Category  | Accessories                |





Fuente de luz (LED) reemplazable por un profesional autorizado

Replaceable (LED only) light source by an authorized professional.

Source lumineuse (LED) remplaçable par un professionnel agréé

Sorgente luminosa (LED) sostituibile da parte di un professionista autorizzato

Austauschbare (LED) Lichtquelle durch einen autorisierten Fachmann



Equipo de control reemplazable por un profesional autorizado

Replaceable control gear by an authorized professional

Dispositif de commande remplaçable par un professionnel agréé

Alimentatore sostituibile da parte di un professionista autorizzato

Auswechselbares Betriebsgerät durch autorisierten Fachmann

INSTRUCCIONES PARA EL FINAL DE VIDA Y LA ELIMINACIÓN LOS COMPONENTES  
 INSTRUCTIONS ON END-OF-LIFE AND COMPONENT DISPOSAL  
 INSTRUCTIONS POUR LA GESTION DES COMPOSANTS EN FIN DE VIE ET LEUR MISE AU REBUT  
 ISTRUZIONI PER IL FINE VITA E LO SMALTIMENTO DEI COMPONENTI  
 ANWEISUNGEN ZUR ENTSORGUNG DER LEUCHTENKOMPONENTEN



Interrumpir la alimentación del aparato  
 Cut the power supply to the luminaire  
 Couper l'alimentation du luminaire  
 Interrompere l'alimentazione dell'apparecchio  
 Stromversorgung der Leuchte unterbrechen



Quitar la(s) fuente(s) de luz para el desecho  
 Remove light source(s) for disposal  
 Retirer la (les) source(s) lumineuse(s) pour l'élimination  
 Rimuovere la/le sorgente/e di luce per lo smaltimento  
 Lichtquelle(n) zur Entsorgung entfernen



Quitar la batería para el desecho  
 Remove the battery for decommissioning  
 Retirer la batterie pour sa mise au rebut  
 Rimuovere la batteria per la dismissione  
 Die Batterie ordnungsgemäß entsorgen



Quitar el equipo de control para el desecho  
 Remove control gear for disposal  
 Retirer le dispositif de commande pour l'élimination  
 Rimuovere l'alimentatore per lo smaltimento  
 Betriebsgerät zur Entsorgung ausbauen



Enviar los materiales a un centro de recogida RAEE  
 Send the materials to a WEEE collection centre  
 Envoyer les matériaux dans une déchetterie DEEE  
 Inviare i materiali ad un centro di raccolta RAEE  
 Die Materialien in einem WEEE-Zentrum entsorgen

