




DIMENSIONS



AWARDS



Name	DRUM 70 DIM DALI 3000K WT
Reference	A2391021WT
Color	Textured white
RAL	9016
Category	SURFACE

PRODUCT

Type	LED
Gross luminous flux	8050 lm
Colour temperature	3000 K
Chromatic stability	MacAdam Step 2
Colour Rendering Index	CRI > 90
Power	59,5 W
Current	700 mA
Efficacy	135 lm/W
LED lifespan	L80B10 > 60.000h

LIGHT SOURCE

Lighting efficiency	87%
Light beam angle	96°

LIGHTING FIXTURE | PHOTOMETRIC DATA

Driver	Included
Power values of the system	66,78 W
Frequency	50/60 Hz
Dimming	DALI
Electrical insulation class	⊕

LIGHTING FIXTURE | ELECTRICAL DATA


Sealing	IP20
Wireless control	Please Consult
Weight	10500 g
Packaged weight	11534,3 g
Packaging dimensions	765 x 765 x 150 mm
Units per package	1
Materials	Aluminium / Polymethyl Methacrylate

OTHER DATA




A large seized ceiling luminaire offering a major luminous flux, either as surface or as suspended fitting, with the possibility to hang it at any desired height. Drum is dimmable in order to be allowed to adapt the light volume at any time exactly to the specific needs of each application or situation. In terms of forms its design is expressed in a surrounding slightly curved circular strip. Counting with a perfect, homogeneous light diffusion and the attractive illusion of a natural skylight.

POLAR DIAGRAM



CONICAL DIAGRAM



UGR

Glare Evaluation According to UGR											
Room Size		70	70	50	50	30	70	70	50	50	30
X Y		Viewing direction at right angles to lamp axis					Viewing direction parallel to lamp axis				
2H	2H	18.1	19.4	18.4	19.6	19.8	18.1	19.4	18.4	19.6	19.8
	3H	19.8	20.9	20.1	21.2	21.5	19.8	20.9	20.1	21.2	21.5
	4H	20.4	21.5	20.8	21.8	22.1	20.4	21.5	20.8	21.8	22.1
	6H	21.0	22.0	21.3	22.3	22.6	21.0	22.0	21.3	22.3	22.6
	8H	21.1	22.1	21.5	22.4	22.7	21.1	22.1	21.5	22.4	22.7
4H	12H	21.3	22.2	21.6	22.5	22.8	21.3	22.2	21.6	22.5	22.8
	2H	18.6	19.7	19.0	20.0	20.3	18.6	19.7	19.0	20.0	20.3
	3H	20.6	21.5	20.9	21.8	22.1	20.6	21.5	20.9	21.8	22.1
	4H	21.4	22.2	21.8	22.5	22.9	21.4	22.2	21.8	22.5	22.9
	6H	22.0	22.7	22.4	23.1	23.5	22.0	22.7	22.4	23.1	23.5
8H	8H	22.3	22.9	22.7	23.3	23.7	22.3	22.9	22.7	23.3	23.7
	12H	22.4	23.0	22.9	23.4	23.9	22.4	23.0	22.9	23.4	23.9
	4H	21.7	22.3	22.1	22.7	23.1	21.7	22.3	22.1	22.7	23.1
12H	6H	22.5	23.0	22.9	23.5	23.9	22.5	23.0	22.9	23.5	23.9
	8H	22.8	23.3	23.3	23.7	24.2	22.8	23.3	23.3	23.7	24.2
	8H	23.1	23.5	23.6	24.0	24.5	23.1	23.5	23.6	24.0	24.5
12H	4H	21.7	22.3	22.2	22.7	23.1	21.7	22.3	22.2	22.7	23.1
	6H	22.6	23.0	23.0	23.5	24.0	22.6	23.0	23.0	23.5	24.0
	8H	22.9	23.3	23.4	23.8	24.3	22.9	23.3	23.4	23.8	24.3
Variation of the observer position for the luminaire distances S											
S = 1.0H		+0.1 / -0.1					+0.1 / -0.1				
S = 1.5H		+0.2 / -0.4					+0.2 / -0.4				
S = 2.0H		+0.4 / -0.7					+0.4 / -0.7				
Standard table		BK06					BK06				
Correction Summand		-2.0					-2.0				
Corrected Glare Indices referring to 8050lm Total Luminous Flux											



Fuente de luz (LED) reemplazable por un profesional autorizado

Replaceable (LED only) light source by an authorized professional.

Source lumineuse (LED) remplaçable par un professionnel agréé

Sorgente luminosa (LED) sostituibile da parte di un professionista autorizzato

Austauschbare (LED) Lichtquelle durch einen autorisierten Fachmann



Equipo de control reemplazable por un profesional autorizado

Replaceable control gear by an authorized professional

Dispositif de commande remplaçable par un professionnel agréé

Alimentatore sostituibile da parte di un professionista autorizzato

Auswechselbares Betriebsgerät durch autorisierten Fachmann

INSTRUCCIONES PARA EL FINAL DE VIDA Y LA ELIMINACIÓN LOS COMPONENTES
 INSTRUCTIONS ON END-OF-LIFE AND COMPONENT DISPOSAL
 INSTRUCTIONS POUR LA GESTION DES COMPOSANTS EN FIN DE VIE ET LEUR MISE AU REBUT
 ISTRUZIONI PER IL FINE VITA E LO SMALTIMENTO DEI COMPONENTI
 ANWEISUNGEN ZUR ENTSORGUNG DER LEUCHTENKOMPONENTEN



Interrumpir la alimentación del aparato
 Cut the power supply to the luminaire
 Couper l'alimentation du luminaire
 Interrompere l'alimentazione dell'apparecchio
 Stromversorgung der Leuchte unterbrechen



Quitar la(s) fuente(s) de luz para el desecho
 Remove light source(s) for disposal
 Retirer la (les) source(s) lumineuse(s) pour l'élimination
 Rimuovere la/le sorgente/e di luce per lo smaltimento
 Lichtquelle(n) zur Entsorgung entfernen



Quitar la batería para el desecho
 Remove the battery for decommissioning
 Retirer la batterie pour sa mise au rebut
 Rimuovere la batteria per la dismissione
 Die Batterie ordnungsgemäß entsorgen



Quitar el equipo de control para el desecho
 Remove control gear for disposal
 Retirer le dispositif de commande pour l'élimination
 Rimuovere l'alimentatore per lo smaltimento
 Betriebsgerät zur Entsorgung ausbauen



Enviar los materiales a un centro de recogida RAEE
 Send the materials to a WEEE collection centre
 Envoyer les matériaux dans une déchetterie DEEE
 Inviare i materiali ad un centro di raccolta RAEE
 Die Materialien in einem WEEE-Zentrum entsorgen

