




## DIMENSIONS



## AWARDS



Name	PUCK RECESSED L DIM DALI/PUSH 4000K WT
Reference	A3132022WT
Color	Textured white
RAL	9016
Category	CEILING RECESSED

Type	LED
Gross luminous flux	1640 lm
Colour temperature	4000 K
Chromatic stability	MacAdam Step 2
Colour Rendering Index	CRI > 90
Power	12 W
Current	350 mA
Efficacy	137 lm/W
LED lifespan	L90B10 > 55.000h

Lighting efficiency	82%
Light beam angle	47°


Driver	Included - Connected
Power values of the system	14,42 W
Frequency	50/60 Hz
Dimming	DALI / Push - Other DIM, please consult
Electrical insulation class	□

Sealing	IP20
Wireless control	Please Consult
Emergency power supply	Please Consult
Recess measurements	Ø86 mm
Weight	514 g
Packaged weight	580 g
Packaging dimensions	192 x 161 x 61 mm
Units per package	1
Materials	Aluminium / Optical Glass




Puck Recessed is the Puck version for recessed applications. Puck Recessed aims to fulfill the functions of general lighting. Its discreet presence takes the shape of a circular piece, totally made of aluminium, with a slight rounded slant to hold the light source back a few centimetres.

POLAR DIAGRAM



CONICAL DIAGRAM



UGR

Glare Evaluation According to UGR																
		70					50					30				
p Ceiling		70	70	50	30	30	70	70	50	30	30	70	70	50	30	30
p Walls		50	30	50	30	30	50	30	50	30	30	50	30	50	30	30
p Floor		20	20	20	20	20	20	20	20	20	20	20	20	20	20	20
Room Size X      Y		Viewing direction at right angles to lamp axis					Viewing direction parallel to lamp axis									
2H	2H	8.2	8.9	8.5	9.1	9.3	7.6	8.3	7.8	8.5	8.7					
	3H	10.6	11.2	10.9	11.5	11.7	10.3	11.0	10.6	11.2	11.4					
	4H	12.1	12.7	12.4	12.9	13.2	11.6	12.2	11.9	12.5	12.8					
	6H	13.0	13.5	13.3	13.8	14.1	12.6	13.1	12.9	13.4	13.7					
	8H	13.5	14.0	13.9	14.3	14.6	13.0	13.5	13.3	13.8	14.1					
4H	2H	8.7	9.3	9.0	9.6	9.8	8.2	8.8	8.5	9.1	9.3					
	3H	11.8	12.3	12.1	12.6	12.9	11.5	12.0	11.9	12.3	12.6					
	4H	13.3	13.8	13.7	14.1	14.4	12.9	13.4	13.3	13.7	14.1					
	6H	14.3	14.7	14.7	15.1	15.4	14.0	14.3	14.4	14.7	15.1					
	8H	15.0	15.3	15.4	15.7	16.1	14.5	14.8	14.9	15.2	15.6					
8H	2H	14.0	14.5	14.3	14.8	15.1	13.4	13.9	13.7	14.2	14.5					
	4H	13.8	14.1	14.2	14.5	14.9	13.5	13.8	13.9	14.2	14.6					
	6H	15.0	15.2	15.5	15.7	16.1	14.7	15.0	15.2	15.4	15.8					
	8H	15.9	16.0	16.2	16.4	16.9	15.4	15.6	15.8	16.0	16.5					
	12H	16.4	16.6	16.9	17.1	17.6	16.0	16.1	16.5	16.6	17.1					
12H	4H	13.9	14.1	14.3	14.5	15.0	13.6	13.9	14.0	14.3	14.7					
	6H	15.2	15.4	15.6	15.8	16.3	14.9	15.1	15.3	15.5	16.0					
	8H	16.0	16.2	16.5	16.6	17.1	15.6	15.8	16.1	16.2	16.7					
Variation of the observer position for the luminaire distances S																
S = 1.0H		+2.7 / -1.1					+2.9 / -1.2									
S = 1.5H		+4.8 / -1.4					+5.0 / -1.6									
S = 2.0H		+6.6 / -1.7					+6.9 / -1.8									
Standard table		BK04					BK04									
Correction																
Summand		-3.4					-3.5									
Corrected Glare Indices referring to 1640lm Total Luminous Flux																



Fuente de luz (LED) reemplazable por un profesional autorizado

Replaceable (LED only) light source by an authorized professional.

Source lumineuse (LED) remplaçable par un professionnel agréé

Sorgente luminosa (LED) sostituibile da parte di un professionista autorizzato

Austauschbare (LED) Lichtquelle durch einen autorisierten Fachmann



Equipo de control reemplazable por un profesional autorizado

Replaceable control gear by an authorized professional

Dispositif de commande remplaçable par un professionnel agréé

Alimentatore sostituibile da parte di un professionista autorizzato

Auswechselbares Betriebsgerät durch autorisierten Fachmann

INSTRUCCIONES PARA EL FINAL DE VIDA Y LA ELIMINACIÓN LOS COMPONENTES  
 INSTRUCTIONS ON END-OF-LIFE AND COMPONENT DISPOSAL  
 INSTRUCTIONS POUR LA GESTION DES COMPOSANTS EN FIN DE VIE ET LEUR MISE AU REBUT  
 ISTRUZIONI PER IL FINE VITA E LO SMALTIMENTO DEI COMPONENTI  
 ANWEISUNGEN ZUR ENTSORGUNG DER LEUCHTENKOMPONENTEN



Interrumpir la alimentación del aparato  
 Cut the power supply to the luminaire  
 Couper l'alimentation du luminaire  
 Interrompere l'alimentazione dell'apparecchio  
 Stromversorgung der Leuchte unterbrechen



Quitar la(s) fuente(s) de luz para el desecho  
 Remove light source(s) for disposal  
 Retirer la (les) source(s) lumineuse(s) pour l'élimination  
 Rimuovere la/le sorgente/e di luce per lo smaltimento  
 Lichtquelle(n) zur Entsorgung entfernen



Quitar la batería para el desecho  
 Remove the battery for decommissioning  
 Retirer la batterie pour sa mise au rebut  
 Rimuovere la batteria per la dismissione  
 Die Batterie ordnungsgemäß entsorgen



Quitar el equipo de control para el desecho  
 Remove control gear for disposal  
 Retirer le dispositif de commande pour l'élimination  
 Rimuovere l'alimentatore per lo smaltimento  
 Betriebsgerät zur Entsorgung ausbauen



Enviar los materiales a un centro de recogida RAEE  
 Send the materials to a WEEE collection centre  
 Envoyer les matériaux dans une déchetterie DEEE  
 Inviare i materiali ad un centro di raccolta RAEE  
 Die Materialien in einem WEEE-Zentrum entsorgen

