Black Foster Micro Custom Surface

Dimensiones



Accesorios

CUSTOM & MOUNTING ACCESSORIES

Premios

PRODUCTO	
Nombre	BLACK FOSTER MICRO CUSTOM MODULE 3 3500K N
Referencia	A4511013N
Color	Negro
RAL	9005
Categoría	CUSTOM SYSTEMS

FUENTE DE LUZ	
Tipo	LED
Flujo luminoso	495 lm
Temperatura de color	3500 K
Estabilidad cromática	MacAdam Step 3
Índice de reproducción cromática	CRI>90
Potencia	4,2 W
Corriente	500 mA
Eficacia	118 lm/W
Horas de vida del LED	L90B10 >60.000h
Eficiencia energética	F

LUMINARIA | DATOS FOTOMÉTRICOS	
Eficiencia lumínica	87%
Ángulo del haz de luz	37°
UGR	< 19

LUMINARIA | DATOS ELÉCTRICOS	
Potencia del sistema	4,97 W
Tensión	48Vdc
Regulación	No Dim
Clase de seguridad eléctrica	II

OTROS DATOS	
Estanqueidad	IP20
Control inalámbrico	Consultar
Tipo de carril	Black Foster Micro Surface Track
Peso	50 g
Peso con embalaje	85 g
Dimensiones embalaje	220 x 48 x 49 mm
Unidades por embalaje	1
Materiales	Aluminio / Acrilonitrilo Butadieno Estireno / Policarbonato

CE

Black Foster Micro es una proeza de ingeniería que traslada el aclamado efecto «The Invisible Black» a una luminaria hiper-reducida. Su diminuto tamaño y finísimo marco ofrecen una estética de 'trimless visual' que se une a una presencia casi inapreciable debido a sus dimensiones compactas. Black Foster Micro está destinado a iluminación general o de acento y puede aplicarse en proyectos que persiguen el mínimo protagonismo de la iluminación en el techo.

Calle N, s/n - Pol. Ind. El Oliveral
46394 Ribarroja del Turia - Valencia (Spain)
info@arkoslight.com - www.arkoslight.com

5 Year GUARANTEE*

Datos lumínicos

Diagrama polar



Diagrama cónico



UGR

Glare Evaluation According to UGR

ρ Ceiling		70	70	50	50	30	70	70	50	50	30
ρ Walls		50	30	50	30	30	50	30	50	30	30
ρ Floor		20	20	20	20	20	20	20	20	20	20
Room Size X	Y	Viewing direction at right angles to lamp axis					Viewing direction parallel to lamp axis				
2H	2H	-2.9	-2.2	-2.6	-2.0	-1.8	-3.6	-2.9	-3.3	-2.7	-2.5
	3H	0.2	0.8	0.5	1.0	1.2	-0.4	0.2	-0.1	0.5	0.7
	4H	2.0	2.5	2.3	2.8	3.0	1.5	2.0	1.8	2.3	2.5
	6H	4.4	4.9	4.8	5.2	5.5	3.3	3.8	3.7	4.1	4.4
	8H	5.4	5.9	5.7	6.2	6.5	4.4	4.9	4.7	5.2	5.5
	12H	6.7	7.2	7.1	7.5	7.8	5.8	6.3	6.1	6.6	6.9
4H	2H	-2.3	-1.7	-2.0	-1.5	-1.2	-2.8	-2.3	-2.5	-2.0	-1.8
	3H	1.2	1.6	1.5	1.9	2.2	0.7	1.1	1.0	1.4	1.7
	4H	3.2	3.6	3.6	3.9	4.3	2.7	3.1	3.0	3.4	3.7
	6H	5.9	6.2	6.3	6.6	7.0	4.8	5.2	5.2	5.5	5.9
	8H	7.0	7.3	7.4	7.7	8.1	6.0	6.3	6.5	6.7	7.1
	12H	8.5	8.7	8.9	9.1	9.5	7.6	7.8	8.0	8.2	8.7
8H	4H	4.0	4.3	4.4	4.6	5.0	3.5	3.8	4.0	4.2	4.6
	6H	6.8	7.0	7.3	7.5	7.9	6.0	6.2	6.5	6.7	7.1
	8H	8.1	8.3	8.6	8.8	9.2	7.4	7.5	7.8	8.0	8.4
	12H	9.8	9.9	10.3	10.4	10.9	9.1	9.3	9.6	9.7	10.2
12H	4H	4.2	4.4	4.6	4.8	5.3	3.8	4.1	4.2	4.5	4.9
	6H	7.1	7.3	7.6	7.7	8.2	6.4	6.6	6.8	7.0	7.5
	8H	8.5	8.7	9.0	9.1	9.6	7.8	8.0	8.3	8.4	8.9

Variation of the observer position for the luminaire distances S

S = 1.0H	+4.7 / -2.2	+4.9 / -2.4
S = 1.5H	+7.4 / -2.5	+7.6 / -2.7
S = 2.0H	+9.4 / -2.8	+9.7 / -3.4
Standard table	---	---
Correction Summand	---	---

Corrected Glare Indices referring to 495lm Total Luminous Flux

Calle N, s/n - Pol. Ind. El Oliveral
46394 Ribarroja del Turia - Valencia (Spain)
info@arkoslight.com - www.arkoslight.com

5 Year GUARANTEE*

Black Foster Micro Custom System components

ARKOSLIGHT

Black Foster Micro Custom System is a modular 48V lighting system designed to create tailored lighting setups by combining tracks, connectors, lighting modules, and accessories. Ideal for projects that demand flexibility, minimalist design, and high performance.

To configure the Black Foster Micro Custom System, you'll need to combine the following components:

1. Tracks – Available in surface or suspended version (using suspension accessories with the surface track), they form the structural and electrical base of the system.

2. Connectors & Power Supply – Join track sections and provide 48V power input.

3. Accessories – Including end caps, joining elements, mounting accessories, and alternative installation parts to secure and finish the system.

Track Options

Choose the track version required for your project configuration.



BLACK FOSTER Micro Custom Surface 1m	A450-01-00-	NT	WT	
BLACK FOSTER Micro Custom Surface 2m	A450-02-00-	NT	WT	
BLACK FOSTER Micro Custom Surface 3m	A450-03-00-	NT	WT	

L-JOINT



T-JOINT



BLACK FOSTER Micro Custom Surface L-Joint	A450-04-00-	NT	WT	
BLACK FOSTER Micro Custom Surface T-Joint	A450-05-00-	NT	WT	
BLACK FOSTER Micro Custom Surface X-Joint	A450-06-00-	NT	WT	

X-JOINT



Complementary track accessories

Use end caps, joiners, and gap covers to connect, close, and cleanly finish your track setup.

			L
BLACK FOSTER Micro Custom Cover Gap 250	A450-00-01-	N	250mm
BLACK FOSTER Micro Custom Cover Gap 500	A450-00-02-	N	500mm
BLACK FOSTER Micro Custom Cover Gap 1000	A450-00-03-	N	1000mm



BLACK FOSTER Micro Custom Surface End	A450-00-04-	N	W

BLACK FOSTER Micro Custom Surface End Feed	A450-00-05-	N	W

BLACK FOSTER Micro Custom Surface Straight Joiner	A450-00-06

COLOUR | NT ■ RAL 9005 | WT □ RAL 9016 | N ■ RAL 9005 | W □ RAL 9016 |

Electrical connections are not included. Please choose the required components from the Connectors section.

Calle N, s/n - Pol. Ind. El Oliveral
46394 Ribarroja del Turia-Valencia (Spain)
info@arkoslight.com - www.arkoslight.com

5 Year GUARANTEE

Black Foster Micro Custom System components ARKOSLIGHT

Connector options

Connectors are required to provide electrical continuity between tracks, ensuring an uninterrupted 48V flow.

Live-End Connector 48V
A338-00-01- | N |



Central Connector 48V
A338-00-02- | N |



L-Joint Connector 48V
A338-00-12- | N |



T-Joint Connector 48V
A450-00-07- | N |



X-Joint Connector 48V
A450-00-08- | N |



Power Supply Options

Select the appropriate power feed to deliver 48V to the system based on your track layout and installation type.

Constant Voltage LED POWER SUPPLY	P	V	D (A x B x C)
0434-01-61* | N |	100W	48V	298 x 19 x 16mm
0434-01-62	150W	48V	350 x 30 x 18mm
0434-01-80	250W	48V	400 x 40 x 22mm

220 240 V~ | *To be installed inside the track.



DROP VOLTAGE TABLE

POWER (W)	CABLE SECTION (mm²)	CABLE LENGTH (m) 5	10	20	30
		TRACK LENGTH (m)			
100	0,75	50	50	X	X
	1,5	50	50	40	25
150	0,75	40	15	X	X
	1,5	50	40	20	X
250	0,75	20	X	X	X
	1,5	35	20	X	X

Connection diagrams:





COLOUR | N ■ RAL 9005 | W □ RAL 9016 |

Calle N, s/n - Pol. Ind. El Oliveral
46394 Ribarroja del Turia-Valencia (Spain)
info@arkoslight.com - www.arkoslight.com

5 Year GUARANTEE

Black Foster Micro Custom System components ARKOSLIGHT

Other accessories

Suspension components

For a suspended configuration, use surface components together with the following accessories:

Black Foster Suspension Kit (2 units)

A450-00-09- | **NT** | **WT** |

Suggested mounting accessories quantities:
1000mm - 2 Pcs.
2000mm - 2 Pcs.
3000mm - 3 Pcs.



Required for remote or integrated driver installation:

Suspension Feed Kit 48V

A338-00-16- | **N** | **W** | NO DIM

A338-00-17- | **N** | **W** | DIM

For remote power supply

A338-00-27- | **N** | **W** | NO DIM

A338-00-28- | **N** | **W** | DIM

For power supply inside the track



For aside box installation replace the power supply:

Wired Power Supply Case 48V

A338-00-25- | **NT** | **WT** | 150W NO DIM

A338-00-26- | **NT** | **WT** | 150W DIM

220
240 V~ INCL



Wire trimless accessories

For installing the suspension system cleanly and discreetly — with no visible ceiling boxes or mounting elements.

FEED

Mains Trimless*

A023-00-01- | **W** | **N** | NO DIM

Mains Thick Trimless*

A023-00-02- | **W** | **N** | DIM

REMOTE INCL Ø20



FASTENING

Steel Cable Trimless*

A023-00-05- | **W** | **N** |

INCL Ø20



* As many pieces as needed ACCORDING to your product

PRODUCT CONFIGURATOR

Use our online configurator to design your own custom product layout. The tool will guide you through the process and automatically calculate the required drivers and accessories.
Start your configuration →

COLOUR | **NT** ■ RAL 9005 | **WT** □ RAL 9016 | **N** ■ RAL 9005 | **W** □ RAL 9016 | **B** □ RAL 9016 |

Calle N, s/n - Pol. Ind. El Oliveral
46394 Ribarroja del Turia-Valencia (Spain)
info@arkoslight.com - www.arkoslight.com

5 Year GUARANTEE

Ecodesign and Energy Labelling

ARKOSLIGHT



Fuente de luz (LED) reemplazable por un profesional autorizado

Replaceable (LED only) light source by an authorized professional.

Source lumineuse (LED) remplaçable par un professionnel agréé

Sorgente luminosa (LED) sostituibile da parte di un professionista autorizzato

Austauschbare (LED) Lichtquelle durch einen autorisierten Fachmann

Equipo de control reemplazable por un profesional autorizado

Replaceable control gear by an authorized professional

Dispositif de commande remplaçable par un professionnel agréé

Alimentatore sostituibile da parte di un professionista autorizzato

Auswechselbares Betriebsgerät durch autorisierten Fachmann

Instrucciones para el final de vida y la eliminación de los componentes:
Instructions on end-of-life and component disposal:
Instructions pour la gestion des composants en fin de vie et leur mise au rebut :
Istruzioni per il fine vita e lo smaltimento dei componenti:
Anweisungen zur entsorgung der Leuchtenkomponenten:

Interrumpir la alimentación del aparato
Cut the power supply to the luminaire
Couper l'alimentation du luminaire
Interrompere l'alimentazione dell'apparecchio
Stromversorgung der Leuchte unterbrechen



Quitar la(s) fuente(s) de luz para el desecho
Remove light source(s) for disposal
Retirer la (les) source(s) lumineuse(s) pour l'élimination
Rimuovere la/le sorgente/e di luce per lo smaltimento
Lichtquelle(n) zur Entsorgung entfernen



Quitar la batería para el desecho
Remove the battery for decommissioning
Retirer la batterie pour sa mise au rebut
Rimuovere la batteria per la dismissione
Die Batterie ordnungsgemäß entsorgen



Quitar el equipo de control para el desecho
Remove control gear for disposal
Retirer le dispositif de commande pour l'élimination
Rimuovere l'alimentatore per lo smaltimento
Betriebsgerät zur Entsorgung ausbauen

Enviar los materiales a un centro de recogida RAEE
Send the materials to a WEEE collection centre
Envoyer les matériaux dans une déchetterie DEEE
Inviare i materiali ad un centro di raccolta RAEE
Die Materialien in einem WEEE-Zentrum entsorgen



Calle N, s/n - Pol. Ind. El Oliveral
46394 Ribarroja del Turia-Valencia (Spain)
info@arkoslight.com - www.arkoslight.com