




DIMENSIONS



| | |
|-----------|--|
| Name | SHOT LIGHT S SPOT DIM PH.CUT 4000K NMG |
| Reference | A4620502NMG |
| Color | Black-Metallized gold |
| RAL | Metallic finish |
| Category | CEILING RECESSED |

| | |
|------------------------|-----------------|
| Type | LED |
| Gross luminous flux | 720 lm |
| Colour temperature | 4000 K |
| Chromatic stability | MacAdam Step 2 |
| Colour Rendering Index | CRI>90 |
| Power | 6 W |
| Current | 500 mA |
| Efficacy | 120 lm/W |
| LED lifespan | L80B10 >60.000h |

| | |
|---------------------|-----|
| Lighting efficiency | 89% |
| Light beam angle | 18° |

| | |
|-----------------------------|---------------------------------------|
| Driver | Included - Connected |
| Power values of the system | 8,28 W |
| Frequency | 50/60 Hz |
| Dimming | Phase Cut - Other DIM, please consult |
| Electrical insulation class | <input type="checkbox"/> |

| | |
|------------------------|---|
| Sealing | IP20 |
| Wireless control | Please Consult |
| Emergency power supply | Please Consult |
| Recess measurements | Ø55 mm |
| Weight | 145 g |
| Packaged weight | 215 g |
| Packaging dimensions | 173 x 85 x 74 mm |
| Units per package | 1 |
| Materials | Aluminium / Acrylonitrile Butadiene Styrene / Polycarbonate |

PRODUCT

SHOT LIGHT S SPOT DIM PH.CUT 4000K NMG

A4620502NMG

Black-Metallized gold

Metallic finish

CEILING RECESSED

LIGHT SOURCE

LED

720 lm

4000 K

MacAdam Step 2

CRI>90

6 W

500 mA

120 lm/W

L80B10 >60.000h

LIGHTING FIXTURE | PHOTOMETRIC DATA

89%

18°

LIGHTING FIXTURE | ELECTRICAL DATA

Included - Connected

8,28 W

50/60 Hz

Phase Cut - Other DIM, please consult

OTHER DATA

IP20

Please Consult

Please Consult

Ø55 mm

145 g

215 g

173 x 85 x 74 mm

1

Aluminium / Acrylonitrile Butadiene Styrene / Polycarbonate



A luminary conceived to be a discreet point of light in the ceiling that hides the illumination source from sight and aims to offer maximum visual comfort. In order to achieve this, it has an anti-glare screen and a specifically designed micro-reflector that generates a perfectly defined light beam.

POLAR DIAGRAM



CONICAL DIAGRAM



UGR

| Glare Evaluation According to UGR | | | | | | | | | | | | |
|--|-----|---|------|------|------|------|--|-------|-------|-------|-------|----|
| p Ceiling | | 70 | 70 | 50 | 50 | 30 | 30 | 70 | 70 | 50 | 50 | 30 |
| p Walls | | 50 | 30 | 50 | 30 | 30 | 30 | 50 | 30 | 50 | 30 | 30 |
| p Floor | | 20 | 20 | 20 | 20 | 20 | 20 | 20 | 20 | 20 | 20 | 20 |
| Room Size X Y | | Viewing direction at right angles to lamp axis | | | | | Viewing direction parallel to lamp axis | | | | | |
| 2H | 2H | -9.4 | -8.8 | -9.2 | -8.6 | -8.4 | -11.3 | -10.7 | -11.1 | -10.5 | -10.3 | |
| | 3H | -7.3 | -6.7 | -7.0 | -6.5 | -6.3 | -6.9 | -6.3 | -6.6 | -6.1 | -5.9 | |
| | 4H | -4.0 | -3.5 | -3.7 | -3.2 | -3.0 | -4.6 | -4.1 | -4.3 | -3.8 | -3.5 | |
| | 6H | -1.8 | -1.3 | -1.5 | -1.0 | -0.7 | -3.4 | -2.9 | -3.1 | -2.6 | -2.3 | |
| | 8H | -0.7 | -0.2 | -0.3 | 0.1 | 0.4 | -0.6 | -0.1 | -0.3 | 0.2 | 0.5 | |
| 4H | 12H | 0.9 | 1.4 | 1.3 | 1.7 | 2.0 | 0.8 | 1.3 | 1.2 | 1.6 | 1.9 | |
| | 2H | -8.9 | -8.3 | -8.6 | -8.1 | -7.8 | -10.3 | -9.8 | -10.0 | -9.5 | -9.2 | |
| | 3H | -6.0 | -5.5 | -5.6 | -5.2 | -4.9 | -5.8 | -5.4 | -5.5 | -5.1 | -4.7 | |
| | 4H | -2.0 | -1.6 | -1.6 | -1.3 | -0.9 | -3.1 | -2.7 | -2.7 | -2.4 | -2.0 | |
| | 6H | 0.1 | 0.4 | 0.5 | 0.8 | 1.2 | -1.7 | -1.4 | -1.3 | -1.1 | -0.7 | |
| 8H | 8H | 1.3 | 1.6 | 1.7 | 1.9 | 2.3 | 1.1 | 1.4 | 1.5 | 1.8 | 2.2 | |
| | 12H | 2.9 | 3.2 | 3.3 | 3.6 | 4.0 | 2.7 | 2.9 | 3.1 | 3.3 | 3.7 | |
| | 4H | -1.4 | -1.1 | -1.0 | -0.8 | -0.4 | -2.2 | -2.0 | -1.8 | -1.6 | -1.2 | |
| | 6H | 0.9 | 1.1 | 1.3 | 1.5 | 2.0 | -0.5 | -0.3 | -0.0 | 0.2 | 0.6 | |
| | 8H | 2.4 | 2.6 | 2.8 | 3.0 | 3.5 | 2.4 | 2.5 | 2.8 | 3.0 | 3.4 | |
| 12H | 12H | 4.3 | 4.5 | 4.8 | 4.9 | 5.4 | 4.2 | 4.3 | 4.7 | 4.8 | 5.3 | |
| | 4H | -1.3 | -1.0 | -0.9 | -0.6 | -0.2 | -2.0 | -1.8 | -1.6 | -1.4 | -1.0 | |
| | 6H | 1.2 | 1.4 | 1.7 | 1.8 | 2.3 | 0.0 | 0.2 | 0.5 | 0.7 | 1.1 | |
| 8H | 2.9 | 3.0 | 3.4 | 3.5 | 4.0 | 2.9 | 3.0 | 3.3 | 3.4 | 3.9 | | |
| Variation of the observer position for the luminaire distances S | | | | | | | | | | | | |
| S = 1.0H | | +1.9 | -0.6 | | | | +1.9 | -0.5 | | | | |
| S = 1.5H | | +3.6 | -0.9 | | | | +3.7 | -1.1 | | | | |
| S = 2.0H | | +5.2 | -1.5 | | | | +5.5 | -1.5 | | | | |
| Standard table Correction Summand | | --- | | | | | --- | | | | | |
| Corrected Glare Indices referring to 720lm Total Luminous Flux | | | | | | | | | | | | |



DRIVER

| | |
|------------|---------------------------|
| 0000-94-44 | DRIVER PHASE CUT 7W 500mA |
|------------|---------------------------|

PHASE CUT DIMMERS TESTED FOR COMPATIBILITY:

| Brand / Manufacturer | Model number | Dimming Type |
|----------------------|---------------|---------------|
| Busch-Jaeger | 6523 U-102 | Trailing edge |
| Busch-Jaeger | 6523 UR-103 | Trailing edge |
| Niko | 310-0190X | Trailing edge |
| Jung | LB-Management | Trailing edge |
| HZC Electric | AU-P3 | Trailing edge |
| Philips | SED-200A | Trailing edge |
| Merten/Schneider | SBD315RC | Trailing edge |
| Etman | ETM327 | Trailing edge |
| Etman | ETM329 | Trailing edge |
| Etman (EGANT) | U321V2 | Trailing edge |
| Casambi | CBU-TED | Trailing edge |

THE PARTICULAR CONDITIONS OF EACH INSTALLATION AND THE SPECIFICATIONS AND CONDITIONS OF USE OF EACH REGULATOR, MAY DIFFER FROM THOSE CONSIDERED IN THE COMPATIBILITY TESTING, AND AFFECT ITS PERFORMANCE IN SAID INSTALLATION.



Fuente de luz (LED) reemplazable por un profesional autorizado

Replaceable (LED only) light source by an authorized professional.

Source lumineuse (LED) remplaçable par un professionnel agréé

Sorgente luminosa (LED) sostituibile da parte di un professionista autorizzato

Austauschbare (LED) Lichtquelle durch einen autorisierten Fachmann



Equipo de control reemplazable por un profesional autorizado

Replaceable control gear by an authorized professional

Dispositif de commande remplaçable par un professionnel agréé

Alimentatore sostituibile da parte di un professionista autorizzato

Auswechselbares Betriebsgerät durch autorisierten Fachmann

INSTRUCCIONES PARA EL FINAL DE VIDA Y LA ELIMINACIÓN LOS COMPONENTES
 INSTRUCTIONS ON END-OF-LIFE AND COMPONENT DISPOSAL
 INSTRUCTIONS POUR LA GESTION DES COMPOSANTS EN FIN DE VIE ET LEUR MISE AU REBUT
 ISTRUZIONI PER IL FINE VITA E LO SMALTIMENTO DEI COMPONENTI
 ANWEISUNGEN ZUR ENTSORGUNG DER LEUCHTENKOMPONENTEN



Interrumpir la alimentación del aparato
 Cut the power supply to the luminaire
 Couper l'alimentation du luminaire
 Interrompere l'alimentazione dell'apparecchio
 Stromversorgung der Leuchte unterbrechen



Quitar la(s) fuente(s) de luz para el desecho
 Remove light source(s) for disposal
 Retirer la (les) source(s) lumineuse(s) pour l'élimination
 Rimuovere la/le sorgente/e di luce per lo smaltimento
 Lichtquelle(n) zur Entsorgung entfernen



Quitar la batería para el desecho
 Remove the battery for decommissioning
 Retirer la batterie pour sa mise au rebut
 Rimuovere la batteria per la dismissione
 Die Batterie ordnungsgemäß entsorgen



Quitar el equipo de control para el desecho
 Remove control gear for disposal
 Retirer le dispositif de commande pour l'élimination
 Rimuovere l'alimentatore per lo smaltimento
 Betriebsgerät zur Entsorgung ausbauen



Enviar los materiales a un centro de recogida RAEE
 Send the materials to a WEEE collection centre
 Envoyer les matériaux dans une déchetterie DEEE
 Inviare i materiali ad un centro di raccolta RAEE
 Die Materialien in einem WEEE-Zentrum entsorgen

