



DIMENSIONS



AWARDS



PRODUCT

Name	BLACK FOSTER REC IP54 5 FLOOD 3000K WN
Reference	A5464011WN
Color	White-Black
RAL	Colour in the mass looks alike RAL 9016 & 9005
Category	CEILING RECESSED

LIGHT SOURCE

Type	LED
Gross luminous flux	1050 lm
Colour temperature	3000 K
Chromatic stability	MacAdam Step 3
Colour Rendering Index	CRI>90
Power	10,5 W
Current	700 mA
Efficacy	100 lm/W
LED lifespan	L90B10 >102.000h

LIGHTING FIXTURE | PHOTOMETRIC DATA

Lighting efficiency	86%
Light beam angle	38°

LIGHTING FIXTURE | ELECTRICAL DATA

Driver	Included - Connected
Power values of the system	12,95 W
Frequency	50/60 Hz
Dimming	No Dim
Electrical insulation class	☐

OTHER DATA

Sealing	IP54
Wireless control	Please Consult
Emergency power supply	Please Consult
Weight	450 g
Packaged weight	545 g
Packaging dimensions	253 x 98 x 50 mm
Materials	Aluminium / Acrylonitrile Butadiene Styrene



Black Foster is the product that transfers the claimed effect "The Invisible Black" to a recessed-isolated lineal luminary; also available in trimless version. If we take a closer view to the recessed model, its bezel is so thin than when lighted up, it is unperceived; offering an aesthetic of "visual trimless". Black Foster stands out for its refinement, its visual comfort and for almost completely hide the source of light from the human eye range.

POLAR DIAGRAM



CONICAL DIAGRAM



UGR

Glare Evaluation According to UGR												
p Ceiling		70	70	50	50	30	70	70	50	50	30	30
p Walls		50	30	50	30	30	50	30	50	30	30	30
p Floor		20	20	20	20	20	20	20	20	20	20	20
Room Size X Y		Viewing direction at right angles to lamp axis					Viewing direction parallel to lamp axis					
2H	2H	-13.7	-13.0	-13.4	-12.8	-12.6	-14.5	-13.9	-14.3	-13.7	-13.5	-13.5
	3H	-7.4	-6.8	-7.1	-6.5	-6.3	-7.2	-6.7	-7.0	-6.4	-6.2	-6.2
	4H	-3.8	-3.3	-3.5	-3.0	-2.8	-3.3	-2.8	-3.0	-2.5	-2.2	-2.2
	6H	-0.2	0.3	0.1	0.6	0.9	0.2	0.7	0.5	0.9	1.2	1.2
	8H	1.6	2.1	2.0	2.4	2.7	2.0	2.4	2.3	2.7	3.0	3.0
4H	12H	3.6	4.1	4.0	4.4	4.7	4.0	4.5	4.3	4.8	5.1	5.1
	2H	-11.1	-10.6	-10.8	-10.3	-10.0	-11.5	-10.9	-11.2	-10.7	-10.4	-10.4
	3H	-5.1	-4.7	-4.8	-4.4	-4.0	-4.9	-4.5	-4.6	-4.2	-3.9	-3.9
	4H	-1.7	-1.3	-1.3	-1.0	-0.6	-1.3	-0.9	-0.9	-0.5	-0.2	-0.2
	6H	1.9	2.2	2.3	2.5	2.9	2.2	2.5	2.6	2.8	3.2	3.2
8H	8H	3.7	4.0	4.1	4.4	4.8	4.0	4.3	4.4	4.7	5.1	5.1
	12H	5.8	6.0	6.2	6.4	6.8	6.1	6.3	6.5	6.7	7.1	7.1
	4H	-0.2	0.1	0.2	0.5	0.9	0.1	0.4	0.5	0.8	1.2	1.2
	6H	3.5	3.7	3.9	4.1	4.6	3.7	3.9	4.1	4.3	4.8	4.8
	8H	5.4	5.6	5.9	6.1	6.5	5.6	5.8	6.1	6.3	6.7	6.7
12H	12H	7.6	7.8	8.1	8.2	8.7	7.9	8.0	8.4	8.5	9.0	9.0
	4H	0.4	0.6	0.8	1.0	1.4	0.6	0.8	1.0	1.2	1.7	1.7
	6H	4.1	4.2	4.5	4.7	5.2	4.2	4.4	4.7	4.9	5.3	5.3
8H	6.1	6.3	6.6	6.8	7.2	6.3	6.5	6.8	6.9	7.4	7.4	
Variation of the observer position for the luminaires distances S												
S = 1.0H		+0.9 / -0.3					+1.3 / -0.4					
S = 1.5H		+1.9 / -0.6					+2.7 / -0.7					
S = 2.0H		+3.1 / -0.8					+4.2 / -1.0					
Standard table Correction Summand							---					

Corrected Glare Indices referring to 1050lm Total Luminous Flux												



Fuente de luz (LED) reemplazable por un profesional autorizado

Replaceable (LED only) light source by an authorized professional.

Source lumineuse (LED) remplaçable par un professionnel agréé

Sorgente luminosa (LED) sostituibile da parte di un professionista autorizzato

Austauschbare (LED) Lichtquelle durch einen autorisierten Fachmann



Equipo de control reemplazable por un profesional autorizado

Replaceable control gear by an authorized professional

Dispositif de commande remplaçable par un professionnel agréé

Alimentatore sostituibile da parte di un professionista autorizzato

Auswechselbares Betriebsgerät durch autorisierten Fachmann

INSTRUCCIONES PARA EL FINAL DE VIDA Y LA ELIMINACIÓN LOS COMPONENTES
INSTRUCTIONS ON END-OF-LIFE AND COMPONENT DISPOSAL
INSTRUCTIONS POUR LA GESTION DES COMPOSANTS EN FIN DE VIE ET LEUR MISE AU REBUT
ISTRUZIONI PER IL FINE VITA E LO SMALTIMENTO DEI COMPONENTI
ANWEISUNGEN ZUR ENTSORGUNG DER LEUCHTENKOMPONENTEN



Interrumpir la alimentación del aparato
Cut the power supply to the luminaire
Couper l'alimentation du luminaire
Interrompere l'alimentazione dell'apparecchio
Stromversorgung der Leuchte unterbrechen



Quitar la(s) fuente(s) de luz para el desecho
Remove light source(s) for disposal
Retirer la (les) source(s) lumineuse(s) pour l'élimination
Rimuovere la/le sorgente/e di luce per lo smaltimento
Lichtquelle(n) zur Entsorgung entfernen



Quitar la batería para el desecho
Remove the battery for decommissioning
Retirer la batterie pour sa mise au rebut
Rimuovere la batteria per la dismissione
Die Batterie ordnungsgemäß entsorgen



Quitar el equipo de control para el desecho
Remove control gear for disposal
Retirer le dispositif de commande pour l'élimination
Rimuovere l'alimentatore per lo smaltimento
Betriebsgerät zur Entsorgung ausbauen

Enviar los materiales a un centro de recogida RAEE
Send the materials to a WEEE collection centre
Envoyer les matériaux dans une déchetterie DEEE
Inviare i materiali ad un centro di raccolta RAEE
Die Materialien in einem WEEE-Zentrum entsorgen

