



Dimensions



Accessories



TRIMLESS ACCESSORY
(MANDATORY)

PRODUCT

Name	BLACK FOSTER TRI 3 SPOT DIM PH.CUT 3000K NMG
Reference	A5583151NMG
Color	Black-Metallized gold
RAL	Metallic finish
Category	CEILING RECESSED

LIGHT SOURCE

Type	LED
Gross luminous flux	630 lm
Colour temperature	3000 K
Chromatic stability	MacAdam Step 3
Colour Rendering Index	CRI>90
Power	6,3 W
Current	700 mA
Efficacy	100 lm/W
LED lifespan	L90B10 >102.000h

LIGHTING FIXTURE | PHOTOMETRIC DATA

Lighting efficiency	90%
Light beam angle	19°

LIGHTING FIXTURE | ELECTRICAL DATA

Driver	Included
Power values of the system	8,81 W
Frequency	50/60 Hz
Dimming	Phase Cut
Electrical insulation class	□


OTHER DATA

Sealing	IP20
Wireless control	Please Consult
Emergency power supply	Please Consult
Recess measurements	49 x 136 mm
Weight	185 g
Packaged weight	265 g
Packaging dimensions	275 x 85 x 70 mm
Units per package	1
Materials	Aluminium / Acrylonitrile Butadiene Styrene




Black Foster is the product that transfers the claimed effect "The Invisible Black" to a recessed-isolated lineal luminary; also available in trimless version. If we take a closer view to the recessed model, its bezel is so thin than when lighted up, it is unperceived; offering an aesthetic of "visual trimless". Black Foster stands out for its refinement, its visual comfort and for almost completely hide the source of light from the human eye range.

Polar diagram



Conical diagram



UGR

Glare Evaluation According to UGR												
ρ Ceiling			70	70	50	50	30	70	70	50	50	30
ρ Walls			50	30	50	30	30	50	30	50	30	30
ρ Floor			20	20	20	20	20	20	20	20	20	20
Room Size X Y			Viewing direction at right angles to lamp axis					Viewing direction parallel to lamp axis				
2H	2H	5.5	6.1	5.7	6.3	6.5	5.5	6.2	5.8	6.4	6.6	
	3H	9.0	9.6	9.3	9.9	10.1	9.1	9.7	9.4	9.9	10.2	
	4H	10.9	11.5	11.2	11.7	12.0	11.0	11.6	11.3	11.8	12.1	
	6H	13.0	13.5	13.3	13.8	14.1	13.0	13.6	13.3	13.8	14.1	
	8H	14.2	14.7	14.6	15.0	15.3	14.3	14.8	14.6	15.1	15.4	
4H	12H	15.6	16.1	15.9	16.4	16.7	15.7	16.2	16.0	16.5	16.8	
	2H	6.5	7.1	6.8	7.3	7.6	6.6	7.1	6.9	7.4	7.7	
	3H	10.3	10.8	10.7	11.1	11.4	10.4	10.9	10.7	11.2	11.5	
	4H	12.4	12.8	12.7	13.1	13.5	12.5	12.9	12.9	13.3	13.6	
	6H	14.6	15.0	15.0	15.4	15.7	14.7	15.0	15.1	15.4	15.8	
8H	16H	16.0	16.3	16.4	16.7	17.1	16.1	16.4	16.5	16.8	17.2	
	12H	17.4	17.7	17.9	18.1	18.5	17.5	17.8	18.0	18.2	18.6	
	4H	13.2	13.5	13.6	13.9	14.3	13.3	13.6	13.7	14.0	14.4	
	6H	15.7	16.0	16.2	16.4	16.8	15.7	16.0	16.2	16.4	16.9	
	8H	17.2	17.4	17.7	17.9	18.3	17.3	17.5	17.8	18.0	18.4	
12H	18H	18.9	19.1	19.4	19.5	20.0	19.0	19.2	19.5	19.6	20.1	
	4H	13.4	13.7	13.9	14.1	14.5	13.5	13.8	14.0	14.2	14.6	
	6H	16.1	16.3	16.6	16.7	17.2	16.1	16.3	16.6	16.8	17.2	
	8H	17.7	17.8	18.2	18.3	18.8	17.7	17.9	18.2	18.4	18.9	
Variation of the observer position for the luminaire distances S												
S = 1.0H S = 1.5H S = 2.0H			+0.2 / -0.2 +0.3 / -0.3 +0.5 / -0.6					+0.2 / -0.2 +0.3 / -0.3 +0.5 / -0.6				
Standard table Correction Summand			---					---				
Corrected Glare Indices referring to 630lm Total Luminous Flux												

MANDATORY FOR INSTALLATION



Model	PRODUCT
Reference	BLACK FOSTER Trimless 3 Accessory
Recess measurements	A560-00-03- W N
	49 X 136
	MANDATORY FOR INSTALLATION

Easy installation

Accessible driver after installation





DRIVER

0433-01-15	DRIVER PH.CUT 700mA
------------	---------------------

PHASE CUT DIMMERS TESTED FOR COMPATIBILITY:

Brand / Manufacturer	Model number	Dimming Type
Busch-Jaeger	6523 U-102	Trailing edge
Busch-Jaeger	6523 UR-103	Trailing edge
Niko	310-0190X	Trailing edge
Jung	LB-Management	Trailing edge
HZC Electric	AU-P3	Trailing edge
Philips	SED-200A	Trailing edge
Merten/Schneider	SBD315RC	Trailing edge
Etman	ETM327	Trailing edge
Etman	ETM329	Trailing edge
Etman (EGANT)	U321V2	Trailing edge
Casambi	CBU-TED	Trailing edge

THE PARTICULAR CONDITIONS OF EACH INSTALLATION AND THE SPECIFICATIONS AND CONDITIONS OF USE OF EACH REGULATOR, MAY DIFFER FROM THOSE CONSIDERED IN THE COMPATIBILITY TESTING, AND AFFECT ITS PERFORMANCE IN SAID INSTALLATION.
FOR MORE INFO, PLEASE CONSULT



Fuente de luz (LED) reemplazable por un profesional autorizado

Replaceable (LED only) light source by an authorized professional.

Source lumineuse (LED) remplaçable par un professionnel agréé

Sorgente luminosa (LED) sostituibile da parte di un professionista autorizzato

Austauschbare (LED) Lichtquelle durch einen autorisierten Fachmann



Equipo de control reemplazable por un profesional autorizado

Replaceable control gear by an authorized professional

Dispositif de commande remplaçable par un professionnel agréé

Alimentatore sostituibile da parte di un professionista autorizzato

Auswechselbares Betriebsgerät durch autorisierten Fachmann

Instrucciones para el final de vida y la eliminación de los componentes:

Instructions on end-of-life and component disposal:

Instructions pour la gestion des composants en fin de vie et leur mise au rebut :

Istruzioni per il fine vita e lo smaltimento dei componenti:

Anweisungen zur entsorgung der Leuchtenkomponenten:



Interrumpir la alimentación del aparato
Cut the power supply to the luminaire
Couper l'alimentation du luminaire
Interrompere l'alimentazione dell'apparecchio
Stromversorgung der Leuchte unterbrechen



Quitar la(s) fuente(s) de luz para el desecho
Remove light source(s) for disposal
Retirer la (les) source(s) lumineuse(s) pour l'élimination
Rimuovere la/le sorgente/e di luce per lo smaltimento
Lichtquelle(n) zur Entsorgung entfernen



Quitar la batería para el desecho
Remove the battery for decommissioning
Retirer la batterie pour sa mise au rebut
Rimuovere la batteria per la dismissione
Die Batterie ordnungsgemäß entsorgen



Quitar el equipo de control para el desecho
Remove control gear for disposal
Retirer le dispositif de commande pour l'élimination
Rimuovere l'alimentatore per lo smaltimento
Betriebsgerät zur Entsorgung ausbauen

Enviar los materiales a un centro de recogida RAEE
Send the materials to a WEEE collection centre
Envoyer les matériaux dans une déchetterie DEEE
Inviare i materiali ad un centro di raccolta RAEE
Die Materialien in einem WEEE-Zentrum entsorgen

