


## DIMENSIONS



## ACCESSORIES



WIRE TRIMLESS ACCESSORY



TRIMLESS TOOL

## PRODUCT

|           |                                      |
|-----------|--------------------------------------|
| Name      | LINE SUSP D&I 1500 DIM PUSH 3000K NT |
| Reference | A4371031NT                           |
| Color     | Textured black                       |
| RAL       | 9005                                 |
| Category  | SUSPENSION                           |

## LIGHT SOURCE

|                        |                        |
|------------------------|------------------------|
| Type                   | LED                    |
| Gross luminous flux    | Up:2140 - Down:3210 lm |
| Colour temperature     | 3000 K                 |
| Chromatic stability    | MacAdam Step 2         |
| Colour Rendering Index | CRI>90                 |
| Power                  | 35 W                   |
| Current                | 1200 mA                |
| Efficacy               | 61 / 92 lm/W           |
| LED lifespan           | L80B10 >60.000h        |

## LIGHTING FIXTURE | PHOTOMETRIC DATA

|                     |      |
|---------------------|------|
| Lighting efficiency | 40%  |
| Light beam angle    | 100° |

## LIGHTING FIXTURE | ELECTRICAL DATA


|                             |          |
|-----------------------------|----------|
| Driver                      | Included |
| Power values of the system  | 39,28 W  |
| Frequency                   | 50/60 Hz |
| Dimming                     | Push     |
| Electrical insulation class | □        |

## OTHER DATA


|                           |                           |
|---------------------------|---------------------------|
| Sealing                   | IP20                      |
| Wireless control          | Please Consult            |
| Recess measurements       | Ø62 mm                    |
| Cord length               | Max. 2 m                  |
| Fast adjustment tensioner | Yes                       |
| Weight                    | 2075 g                    |
| Packaged weight           | 3060 g                    |
| Packaging dimensions      | Ø105 x 1820 mm            |
| Units per package         | 1                         |
| Materials                 | Aluminium / Polycarbonate |

Line Suspension is an elegant luminaire composed of a linear light which can combine direct and indirect light... Its pure volumes – a diffuser inserted in the aluminium core – and its miniaturised components make its integration into the architectural space extraordinary. The range consists of 3 versions: Line Suspension, Line Suspension Direct&Indirect and a Micro version. All these products are available in two lengths.

POLAR DIAGRAM



CONICAL DIAGRAM



# WIRE TRIMLESS ACCESSORY


ARKOSLIGHT®

## LINE SUSPENSION & LINE MICRO SUSPENSION

### FEED




| PRODUCT   |                                                                           |
|-----------|---------------------------------------------------------------------------|
| Model     | Coaxial Trimless                                                          |
| Reference | A023-00-03-   W   N                                                       |
| Colour    | W <input type="checkbox"/> RAL 9016   N <input type="checkbox"/> RAL 9005 |
| Category  | Accessories                                                               |



### FASTENING



| PRODUCT   |                                                                           |
|-----------|---------------------------------------------------------------------------|
| Model     | Steel Cable Trimless                                                      |
| Reference | A023-00-05-   W   N                                                       |
| Colour    | W <input type="checkbox"/> RAL 9016   N <input type="checkbox"/> RAL 9005 |
| Category  | Accessories                                                               |



Wire Trimless Accessory is a collection of accessories for fitting tensioners and cables to Arkoslight luminaires suspended directly from the ceiling with any visible ceiling rose or fixings. This achieves a minimalist application with a visually tidy finish.

With Wire Trimless Accessory the items adjacent to the ceiling of the standard product (ceiling roses, fixings, driver boxes, etc.) are concealed by a simple recessed application.

Wire Trimless Accessory reduces the visual impact of the installation leading to extremely minimalist aesthetics. The wires come out of the ceiling material as a part of the structure. This detail creates a much purer, more essential layout, particular when several luminaires are fitted in an arrangement.





## INSTALLATION GUIDE


[https://youtu.be/sa\\_xAgj4ji4](https://youtu.be/sa_xAgj4ji4)



## PRODUCT

|           |                                   |
|-----------|-----------------------------------|
| Model     | Trimless Tool <b>D20 X D52 MM</b> |
| Reference | A478-00-01                        |
| Category  | Accessories                       |





Fuente de luz (LED) reemplazable por un profesional autorizado

Replaceable (LED only) light source by an authorized professional.

Source lumineuse (LED) remplaçable par un professionnel agréé

Sorgente luminosa (LED) sostituibile da parte di un professionista autorizzato

Austauschbare (LED) Lichtquelle durch einen autorisierten Fachmann



Equipo de control reemplazable por un profesional autorizado

Replaceable control gear by an authorized professional

Dispositif de commande remplaçable par un professionnel agréé

Alimentatore sostituibile da parte di un professionista autorizzato

Auswechselbares Betriebsgerät durch autorisierten Fachmann

## INSTRUCCIONES PARA EL FINAL DE VIDA Y LA ELIMINACIÓN LOS COMPONENTES

### INSTRUCTIONS ON END-OF-LIFE AND COMPONENT DISPOSAL

### INSTRUCTIONS POUR LA GESTION DES COMPOSANTS EN FIN DE VIE ET LEUR MISE AU REBUT

### ISTRUZIONI PER IL FINE VITA E LO SMALTIMENTO DEI COMPONENTI

### ANWEISUNGEN ZUR ENTSORGUNG DER LEUCHTENKOMPONENTEN



Interrumpir la alimentación del aparato

Cut the power supply to the luminaire

Couper l'alimentation du luminaire

Interrompere l'alimentazione dell'apparecchio

Stromversorgung der Leuchte unterbrechen




Quitar la(s) fuente(s) de luz para el desecho

Remove light source(s) for disposal

Retirer la (les) source(s) lumineuse(s) pour l'élimination

Rimuovere la/le sorgente/e di luce per lo smaltimento

Lichtquelle(n) zur Entsorgung entfernen



Quitar la batería para el desecho

Remove the battery for decommissioning

Retirer la batterie pour sa mise au rebut

Rimuovere la batteria per la dismissione

Die Batterie ordnungsgemäß entsorgen



Quitar el equipo de control para el desecho

Remove control gear for disposal

Retirer le dispositif de commande pour l'élimination

Rimuovere l'alimentatore per lo smaltimento

Betriebsgerät zur Entsorgung ausbauen

Enviar los materiales a un centro de recogida RAEE

Send the materials to a WEEE collection centre

Envoyer les matériaux dans une déchetterie DEEE

Inviare i materiali ad un centro di raccolta RAEE

Die Materialien in einem WEEE-Zentrum entsorgen

